

Model Name	Camcorder Interface for Microphone				Applicable Shotgun Microphone (Stereo/Mono)	Applicable Shotgun Microphone (Mono)	Applicable Wireless Tuner				Applicable Wireless Tuner	
	Built-in Wireless Slot	DC Output for Wireless Tuner	Front	Rear			WRR-855A/855B/855S (1 ch) for Slot-in	WRR-855A/855B/855S (1 ch) for mounting on rear position	WRR-861A/861B (1 ch)	WRR-862A/862B (2 ch)	Digital (2 ch) for Slot-in	Digital (2 ch) for mounting on rear position
			Mic Input Connector	Mic/Line Input Connector								
<b>HDCAM Camcorders</b>												
HDW-F900R HDW-790/790P	Yes	Yes	XLR-5pin x1	XLR-3pin x2(*3)	ECM-680S	ECM-678 Requires XLR-3P - XLR-5P Cable(K-1502)	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
HDW-730S	Yes	Yes	XLR-3pin x1	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
<b>Digital Betacam Camcorders</b>												
DW-970/970P	Yes	Yes	XLR-3pin x1	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
<b>MPEG IMX Camcorders</b>												
MSW-970/970P	Yes	Yes	XLR-3pin x1	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
<b>XDCAM Camcorders</b>												
PDW-510/510P PDW-530/530P	Yes	Yes	XLR-3pin x1	XLR-3pin x2(*3)	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678 ECM-674(*1) ECM-673	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
<b>XDCAM HD Camcorders</b>												
PDW-F335L PDW-F335L/K	No	Yes	XLR-5pin x1	XLR-3pin x2	ECM-680S	ECM-678 ECM-674(*1) ECM-673 Requires XLR-3P - XLR-5P Cable(K-1502)	Requires CA-WR855 Mount Adaptor *2	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
PDW-700/740	Yes	Yes	XLR-5pin x1	XLR-3pin x2(*3)	ECM-680S	ECM-678 ECM-674(*1) ECM-673 Requires XLR-3P - XLR-5P Cable(K-1502)	Direct slot-in	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket	Direct slot-in	Requires A-8278-057-B Mount Bracket and DWA-01D: Direct Slot-in + Max Tunit
<b>DVCAM Camcorders</b>												
DSR-400/400P DSR-450WS/450WSP	No	Yes	XLR-3pin x1	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-674(*1) ECM-673	Requires CA-WR855 Mount Adaptor *2	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
DSR-250/250P	No	Yes	XLR-3pin x1	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678 ECM-674(*1) ECM-673	-	Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit
<b>HDV Camcorders</b>												
HVR-S270	No	Yes	XLR-3pin x2	XLR-3pin x2	ECM-680S Requires XLR-5P - XLR-3P(2) Cable(K-1504)	ECM-678 ECM-674(*1) ECM-673		Requires A-8278-057-B Mount Bracket and BTA-801or DWA-01D	Requires A-8278-057-B Mount Bracket	Requires A-8278-057-B Mount Bracket		Requires A-8278-057-B Mount Bracket and DWA-01D: Max Tunit

\*1 : The ECM-674 can be driven by external DC power(40 to 52V) or battery(AA-size).

\*2 : Recommend to use the BTA-801 or DWA-01D when using with 3rd party battery.

\*3 : AES/EBU input can be selected for digital connection.